

## LM-MICPRE EXTERNAL MIC PREAMP

### FEATURE OVERVIEW

- USB powered
- Use external dynamic mic with Intercom
- External gain knob
- Always on, latch, push to talk modes on Intercom
- Works with FP-2 footswitch

The Livemix LM-MICPRE is a USB powered microphone preamp that provides the ability to use an external dynamic microphone with the built-in intercom system. Using an external mic with the intercom allows musical directors and team members to communicate clearly while saving channels on the personal mixers or console.



When using an external mic for the intercom, the intercom button or FP-2 foot pedal can be configured in one of three different modes – always on, latch or momentary (push to talk).

**INCLUDES:** LM-MICPRE unit, thumbscrews or phillips head screws for mounting to MT-1, USB power cable, 1/8" cable, rubber pads.

### LM-MICPRE

Dimensions	3.75" (92mm) W 2.75" (70mm) D 1.125" (32mm) H
Weight	.38 lb (.17kg)
Gain	47dB
THD+N	95dB
Frequency Response	20 Hz - 20kHz
EIN	-127 dB
Max input level	-5dBu
Max Output	0 dBu
Input impedance	1.8 KΩ



**FOR ORDERS CONTACT:**  
sales@digitalaudio.com  
Phone: 952-401-7700

**DIGITAL AUDIO LABS**  
1266 PARK RD CHANHASSEN, MN 55317  
WWW.DIGITALAUDIO.COM